



IMPORTANT

Disconnect power before installing fixtures. Read instructions before starting work. This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.

MUST BE INSTALLED BY A QUALIFIED ELECTRICIAN.

Tessaera 3303/3403 Wall Mount

INSTALLATION INSTRUCTIONS

1. Remove luminaire from carton.
2. Remove (4) flat head screws located on the sides of the housing assembly. Remove mounting plate.
3. Position mounting plate over a standard 4" octagon junction box (by others), ensure mounting plate is centered and 'true' vertical when mounting. (2) #8-32 flat head philips drive screws are provided to mount to the ears of the junction box (see mounting plate detail).
4. Alternatively, if the junction box ears are not able to be aligned to ensure fixture is 'true' vertical, use the outboard mounting holes provided and independently attach the mounting plate to the wall surface through the 7/32" holes provided. Must use #10 pan head type screw suitable for your wall conditions (hardware by others).
5. Connect the black(+), white(-) and green wire leads from the housing to the supply leads from the junction box and push these connections carefully in to the junction box.
6. The housing assembly is now placed on to the mounting plate and is secured with the (4) flat head screws removed in step 2. Ensure assembly is secured against wall surface.
7. Energize and test as required.
8. This fixture is supplied with an LED as specified for the project and is self contained.